

# Portable Product Sheet - Voice Density



Last Updated: November 5, 2002

## Number of Voice Interfaces per Platform

The densities below are based on physical ports, the amount of supported calls per device will vary depending on which codec is used.

Platform	Voice Interface Type					
	Analog FXS	Analog FXO	Analog E&M	Analog DID	Digital PRI/T1/E1	Digital ISDN-BRI
ATA186	2	No	No	No	No	No
IAD2400	16	8	No	8	No	1
827-4V	4	No	No	No	No	No
1751	6 (12*)	6	6	4	1	6
1760	8 (16*)	8	8	8	1	8
<b>2600XM</b>						
NM-2V	4	4	4	4	No	2
NM-HDA	12	8	No	No	No	No
NM-HDV	No	No	No	No	2	No
AIM-VOICE-30	No	No	No	No	1	No
<b>2691</b>						
NM-2V	4	4	4	4	No	2
NM-HDA	12	8	No	No	No	No
NM-HDV	No	No	No	No	2	No
AIM-VOICE-30	No	No	No	No	1**	No
<b>3620</b>						
NM-2V	4	4	4	4	No	2
NM-HDA	12	8	No	No	No	No
NM-HDV	No	No	No	No	2	No
<b>3640</b>						
NM-2V	12	12	12	12	No	6
NM-HDA	36	24	No	No	No	No
NM-HDV	No	No	No	No	6	No
<b>3660</b>						
NM-2V	24	24	24	24	No	12
NM-HDA	72	48	No	No	No	No
NM-HDV	No	No	No	No	12	No
AIM-VOICE-30	No	No	No	No	2	No
<b>3725</b>						
NM-2V	8	8	8	8	No	4
NM-HDA	24	16	No	No	No	No
NM-HDV	No	No	No	No	4	No
AIM-VOICE-30	No	No	No	No	2**	No
<b>3745</b>						
NM-2V	16	16	16	16	No	8
NM-HDA	48	32	No	No	No	No
NM-HDV	No	No	No	No	8	No
AIM-VOICE-30	No	No	No	No	2**	No

# Portable Product Sheet - Voice Density



Platform	Voice Interface Type					
	Analog FXS	Analog FXO	Analog E&M	Analog DID	Digital PRI/T1/E1	Digital ISDN-BRI
<b>VG2xx</b>						
<b>VG248</b>	48	No	No	No	No	No
<b>VG200</b>						
<b>NM-2V</b>	4	4	4	4	No	2
<b>NM-HDV</b>	No	No	No	No	2	No
<b>AS5xx0</b>						
<b>AS5350</b>	No	No	No	No	8	No
<b>AS5400</b>	No	No	No	No	16/28***	No
<b>Cat4000</b>						
<b>WS-X4604-GWY</b>	14	6	6		2	6
<b>Cat6000</b>						
<b>WS-X6624-FXS</b>	24	No	No	No	No	No
<b>WS-X6608</b>	No	No	No	No	8	No
<b>WS-SVC-CMM</b>	72	No	No	No	18	No
<b>7x00</b>						
<b>7200</b>	No	No	No	No	18	No
<b>ICS7750</b>						
<b>MRP300</b>	8	8	4	8	2	4
<b>MRP3-8FXS</b>	8	4	2	4	1	2
<b>MRP3-16FXS</b>	16	No	No	No	No	No

\* When support added for VIC-4FXS/DID

\*\* When support added for AIM-VOICE-30

\*\*\* When using a CT3 interface instead of individual T1s